



8000 Watts†

10000 Starting Watts††

Specifications

- Briggs & Stratton OHV Engine, 420cc
- StatStation Wireless
 - Run Time
 - Percent Load
 - Unit Hours
 - Maintenance Reminders
- Multi-Featured Control Panel
 - 4-120V GFCI Protected Household Outlets
 - 1-120V/240V 30A Locking Outlet
 - Hour Meter & Protective Outlet Covers
- 7.5 Gallon Metal Fuel Tank with Fuel Gauge
 - Provides up to a 9 Hour Run-Time at ½ Load
- Power Surge™ Alternator
 - Produces the power needed to start & keep appliances and tools running simultaneously
- Key Electric Start & Remote Choke
- 12" Never Go Flat Wheels



Model: 030664

3-Year Limited Warranty



ELITE Series™

FAST TRACK

Product Line



Running Watts	7000	8000
Starting Watts	8750	10000
Engine Brand	Briggs & Stratton 2100 Series™	Briggs & Stratton 2100 Series™
Engine Rating	420cc	420cc
Runtime @ ½ Load	9 hours	9 hours
Fuel Tank Capacity	7.5 gallon	7.5 gallon
Wheels	12" Never Go Flat	12" Never Go Flat
Outlet Configuration	4-120V 1-120V/240V-30A	4-120V 1-120V/240V-30A
Other Features	Key Electric Start Hour Meter Outlet Covers	Key Electric Start Hour Meter Outlet Covers

†Wattage per PGMA G200-2013

††Starting Watt-This generator is rated in accordance with Briggs & Stratton



Running Watts*	8000
Starting Watts*	10000
Volts	120/240
Running Amps	33.3
Surge Amps	66.6
Engine Brand	Briggs & Stratton®
Engine Displacement (cc)	420
OHV Engine	Yes
Fuel Tank Capacity (gal)	7.5
Run Time	Up to 9 hours
Alternator	Power Surge™
Start Type	Electric/Recoil
Low Oil Shutdown	Yes
Automatic Idle Control	No
Muffler	Super Lo-Tone™
Fuel Gauge	Yes
Hour Meter	Yes
Wheel Type	Never Go Flat
Wheel Diameter (in)	12.0
Weight (lbs)	248
Length (in)	28
Width (in)	31
Height (in)	29
Consumer Warranty (Product) **	3-year Limited
Commercial Warranty (Product) **	90-day Limited